

AD-A284 525


NPSEC-94-009



1

NAVAL POSTGRADUATE SCHOOL

Monterey, California



TLS-Based Prefiltering Technique for Time-Domain ARMA Modeling

by

Monique P. Fargues

August 15, 1994

94-30000

Approved for public release; distribution unlimited.

Prepared for: Office of Naval Research

DTIC QUALITY INSPECTED

94 8 16 001

Naval Postgraduate School
Monterey, California 93943-5000


Rear Admiral T. A. Mercer
Superintendent

H. Shull
Provost

This report was funded by the Office of Naval Research.

Approved for public release; distribution unlimited.

This report was prepared by:



Monique P. Fargues
Assistant Professor,
Department of Electrical and
Computer Engineering

Reviewed by:

Released by:



MICHAEL A. MORGAN
Chairman,
Department of Electrical and
Computer Engineering



PAUL J. MARTO
Dean of Research

REPORT DOCUMENTATION PAGE

Form Approved
OMB No. 0704-0188

Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503.

1. AGENCY USE ONLY (Leave blank)

2. REPORT DATE

August 15, 1994

3. REPORT TYPE AND DATES COVERED

Final Report Oct 1, 1993-Sep 30, 1994

4. TITLE AND SUBTITLE

TLS-Based Prefiltering Technique for Time-Domain ARMA Modeling

5. FUNDING NUMBERS

6. AUTHOR(S)

Monique P. Fargues

7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES)

Naval Postgraduate School
Monterey, CA 93943-5000

8. PERFORMING ORGANIZATION
REPORT NUMBER

NPSEC-94-009

9. SPONSORING / MONITORING AGENCY NAME(S) AND ADDRESS(ES)

Office of Naval Research
Code 1114
Arlington, VA 22217-5000

10. SPONSORING / MONITORING
AGENCY REPORT NUMBER

11. SUPPLEMENTARY NOTES

The views expressed in this report are those of the authors and do not reflect the official policy or position of the Department of Defense or the United States Government.

12a. DISTRIBUTION / AVAILABILITY STATEMENT

Approved for public release; distribution unlimited.

12b. DISTRIBUTION CODE

13. ABSTRACT (Maximum 200 words)

Modeling time-series with linear pole-zero AutoRegressive-Moving Average (ARMA) models has numerous applications in signal processing. This problem is in general non-linear and most ARMA modeling techniques are iterative in nature. The Iterative Prefiltering (IP) method has the advantage of computing potential non-minimum phase representations which may be useful in time-domain modeling. The original IP minimization procedure is an ill-conditioned problem which has classically been solved using a least-squares approach. This work presents a modification of the classical IP technique in which the least-squares iteration step is replaced by a Total Least Squares (TLS) step to take advantage of the statistical properties of the TLS method. Results show that improvements in the modeling performances may be obtained by using the TLS-based IP method when modeling signals distorted by white Gaussian noise.

14. SUBJECT TERMS

ARMA modeling, total least squares, transient modeling

15. NUMBER OF PAGES
19

16. PRICE CODE

17. SECURITY CLASSIFICATION
OF REPORT

UNCLASSIFIED

18. SECURITY CLASSIFICATION
OF THIS PAGE

UNCLASSIFIED

19. SECURITY CLASSIFICATION
OF ABSTRACT

UNCLASSIFIED

20. LIMITATION OF ABSTRACT

SAR

TLS-BASED PREFILTERING TECHNIQUE FOR TIME-DOMAIN ARMA MODELING

Monique P. Fargues

**Electrical and Computer Engineering Department
Naval Postgraduate School
Monterey, CA 93943-5121**

August 15, 1994

**Research Sponsored by
Office of Naval Research
Code 1114
Arlington, VA 22217-5000**

Accession For	
NTIS GRA&I	<input checked="checked" type="checkbox"/>
DTIC TAB	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
By	
Distribution	
Availability Codes	
Dist	Avail and/or Special

1. Introduction

Modeling time-series with linear pole-zero AutoRegressive-Moving Average (ARMA) models has numerous applications in signal processing. This problem is in general non linear and most ARMA modeling techniques are iterative in nature. The Iterative Prefiltering (IP) method has the advantage of computing potential non-minimum phase representations which may be useful in time-domain modeling. The original IP minimization procedure is an ill-conditioned problem which has classically been solved using a least-squares approach. This work presents a modification of the classical IP technique in which the least-squares iteration step is replaced by a Total Least Squares (TLS) step to take advantage of the statistical properties of the TLS method. Results show that improvements in the modeling performances may be obtained by using the TLS-based IP method when modeling signals distorted by white Gaussian noise.

Section 2 presents a review of the TLS method, and illustrates its main advantages as compared to the LS method. Next, Section 3 presents the classical Iterative Prefiltering method and the proposed TLS-based IP method. Finally, conclusions are given in Section 4.

2. Total Least Squares Problem

2.1 Introduction

The Total Least Squares method (TLS) has been introduced recently as a substitute to the classical Least Squares (LS) method for solving overdetermined linear systems of equations when all data involved in the computation are corrupted with noise (errors) [1,2]. Consider the problem of solving the overdetermined system of equations $A\underline{x} = \underline{b}$, where A has dimension $m \times n$ and \underline{b} has dimension $m \times 1$. The LS solution \underline{x}_{ls} is obtained by minimizing the Euclidean norm $\|A\underline{x} - \underline{b}\|_2$. Solving for the LS solution is equivalent to solving the following minimization problem:

$$\begin{aligned} & \text{minimize}_{\underline{b}' \in \mathbb{R}^m} \quad \|\underline{b} - \underline{b}'\|_2 \\ & \text{subject to} \quad \underline{b}' \in R(A) \end{aligned}$$

The above equation is satisfied when \underline{b}' is the orthogonal projection of \underline{b} onto $R(A)$. Thus, the LS vector \underline{b}' can be viewed as the perturbation of \underline{b} so that \underline{b}' can be generated by the range (or the column space) of A . As a consequence, the LS solution assumes that errors can occur only in the vector \underline{b} and not in the matrix A . However, this assumption is not always realistic as errors such as sampling, modeling, and instrumentation errors may force inaccuracies in A also. The TLS takes into account the fact that errors may occur both in the matrix A and in the vector \underline{b} and solves the following minimization problem:

$$\begin{aligned} & \text{minimize}_{[\hat{A}; \hat{\underline{b}}] \in \mathbb{R}^{m \times (n+1)}} \quad \|[A; \underline{b}] - [\hat{A}; \hat{\underline{b}}]\|_2 \\ & \text{subject to} \quad \hat{\underline{b}} \in R(\hat{A}) \end{aligned}$$

Thus, the TLS vector $\hat{\underline{b}}$ can be viewed as resulting from the perturbation both from the columns of

A and the vector b so that \hat{b} belongs to $R(\hat{A})$. An illustration of the differences between the LS and the TLS solution for a system with column space of dimension two is shown in Figure 1.

2.2 SVD-Based Solution of the TLS Problem

The Singular Value Decomposition (SVD) is used to solve the TLS problem [1,2]. Recall that the system to be solved is of the form $Ax=b$, which can be reformulated as:

$$[A;b] \begin{bmatrix} x \\ -1 \end{bmatrix} \approx 0.$$

The TLS solution is found from the SVD of the augmented matrix

$$C = [A;b] = U\Sigma V^H.$$

The solution is said to be generic or non generic depending on the numerical characteristics of the eigenvalue matrix Σ and the right singular vector matrix V .

2.2.a TLS Generic Solution

The TLS solution x_{TLS} is unique and said to be generic if the singular value $\sigma_n > \sigma_{n+1}$ and $v_{n+1,n+1} \neq 0$. In such a case the solution is given by:

$$x_{TLS} = -1/v_{n+1,n+1} [v_{1,n+1}, \dots, v_{n,n+1}]^T.$$

When the p smallest singular values are equal, i.e., $\sigma_{n-p} > \sigma_{n-p+1} = \dots = \sigma_{n+1}$, the TLS solution to the linear system is not unique, and any linear combination of the singular vectors associated with the multiple minimum singular value can be chosen provided that it is normalized properly. The resulting minimum norm solution can be shown to be equal to [1,3]

$$x_{TLS} = -\frac{\hat{V}_2 c}{c^T c} = \frac{\hat{V}_1 g}{1 - g^T g}.$$

Matrices \hat{V}_1 and \hat{V}_2 are submatrices of the matrices of the right singular vector matrices V_1 and V_2 , where V_2 is the matrix of right singular vectors associated with the multiple minimum singular value, and V_1 contained all the other right singular vectors. \hat{V}_1 and \hat{V}_2 are defined as:

$$V_2 = \begin{bmatrix} c^T \\ \hat{V}_2 \end{bmatrix}, \text{ and } V_1 = \begin{bmatrix} g^T \\ \hat{V}_1 \end{bmatrix},$$

where the vectors c^T and g^T respectively represent the first row of V_2 and V_1 .

Again, the TLS solution exists only if all $v_{n+1,i} \neq 0$ for $i = n-p+1, \dots, n+1$. Van Huffel showed that no generic solution exists only when the matrix A is nearly rank deficient, or when the set of equations is conflicting [4]. The set of equations is said to be conflicting when $\sigma_{n-p+1} \approx \dots \approx \sigma_{n+1}$ are large. In such a case, trying to model the data using a linear model is inaccurate, and a better

option should be chosen by the user. When $\sigma_{n-p+1} \approx \dots \approx \sigma_{n+1}$ are small, two options are possible. The first option for the user is to remove dependent columns of A to reset the problem so that the resulting modified A matrix is regular, and to solve a generic TLS problem. How to pick such columns is addressed in [2,14]. The second option is to solve a nongeneric TLS problem which is obtained from adding additional constraints on the generic TLS problem in order for it to be solvable.

2.2.b The Nongeneric TLS Problem

The nongeneric TLS problem is addressed in details in Van Huffel et al. [4,5,7]. The resulting solution is given by:

$$\mathbf{x}_{\text{TLS}} = -1/v_{n+1,n-p} [v_{1,n-p}, \dots, v_{n,n-p}]^t,$$

when $\sigma_{n-p} > \sigma_{n-p+1} = \dots = \sigma_{n+1}$, $v_{n+1,i} = 0$ for $i = n-p+1, \dots, n+1$, and $v_{n+1,n-p} \neq 0$.

2.3 Applications of the TLS to Signal Processing Problems

Numerous researchers in Signal Processing have reformulated problems in terms of the TLS technique. Applications can be found in array processing [11], in system modeling [10], and in frequency estimation of sinusoidal signals [9,10-13] for example. Results show that improvements in the performances can be obtained when reformulating LS problems in a TLS set-up for the applications mentioned above. This result motivated our investigation of the TLS technique to time-series data modeling. ARMA modeling of time-series is a non-linear problem which has been extensively studied in the literature [17]. The Iterative Prefiltering (IP) method is an iterative linearized formulation which was originally proposed by Steiglitz and McBride to identify linear system transfer functions [15,16], and the IP method can be reformulated to model time-series data distorted with noise. Note that the method is not insured to converge to the optimal solution and De Moor showed that it converges to a suboptimal solution only [18]. Nevertheless, simulation results have shown that useful models can still be obtained using the IP method [19].

3. The Iterative Prefiltering Method

3.1 Introduction

The Iterative Prefiltering method attempts to model a time-series data with an ARMA(P,Q) system using a time-domain approach by minimizing the error between the data and the impulse response of the system to be estimated. Using the Z-domain, the model function is given by:

$$H(z) = \frac{B(z)}{A(z)},$$

where

$$A(z) = \sum_{k=0}^p a(k)z^{-k} \text{ and } B(z) = \sum_{k=0}^p b(k)z^{-k}.$$

The error function for the problem is defined by

$$E(z) = X(z) - \frac{B(z)}{A(z)} = \frac{X(z)A(z) - B(z)}{A(z)}. \quad (1)$$

Non-linearity in the problem is due to the denominator $A(z)$ in the error function $E(z)$. The problem may be linearized by replacing the error function given in eq. (1) with the iterative error function

$$E^{(i)}(z) = \frac{X(z)A^{(i)}(z) - B^{(i)}(z)}{A^{(i-1)}(z)},$$

where indices (i) and (i-1) refer to iterations (i) and (i-1). At each iteration the quantities $A^{(i)}(z)$ and $B^{(i)}(z)$ are chosen to minimize the error $E^{(i)}(z)$. The estimation of the ARMA transfer function is done in the time domain using the time series $x(n)$, for $n=0, \dots, N-1$, by rewriting $E^{(i)}(z)$ in the time-domain as

$$E^{(i)}(n) = \underline{x}^{(i)H}(n) * \underline{a}^{(i)} - \underline{h}^{(i)H}(n) \cdot \underline{b}^{(i)}, \quad n=0, \dots, N-1 \quad (2)$$

with:

$$E^{(i)}(n) = \underline{x}^{(i)}(n)^H \cdot \underline{a}^{(i)} - \underline{h}^{(i)H}(n) \cdot \underline{b}^{(i)} \quad n=0, \dots, N-1$$

$$\underline{x}^{(i)}(n) = [x^{(i)}(n), \dots, x^{(i)}(n-P)]^T$$

$$\underline{h}^{(i)}(n) = [h^{(i)}(n), \dots, h^{(i)}(n-Q)]^T$$

$$\underline{a}^{(i)} = [1, a^{(i)}(1), \dots, a^{(i)}(P)]$$

$$\underline{b}^{(i)} = [b^{(i)}(0), \dots, b^{(i)}(Q)]$$

where $h^{(i)}(n)$ is the impulse response of $H^{(i)}(z) = 1/A^{(i)}(z)$, and $x^{(i)}(n)$ represents the output of $x(n)$ through the filter $H^{(i)}(z)$. Eq. (2) expressed in matrix form becomes:

$$\underline{E}^{(i)} = \begin{bmatrix} 0 & \dots & \dots & x^{(i)}(0) \\ 0 & \dots & x^{(i)}(0) & x^{(i)}(1) \\ \vdots & \dots & \vdots & \dots \\ x^{(i)}(N-P) & \dots & x^{(i)}(N-2) & x^{(i)}(N-1) \end{bmatrix} \begin{bmatrix} a^{(i)}(P) \\ a^{(i)}(P-1) \\ \vdots \\ 1 \end{bmatrix} - \begin{bmatrix} h^{(i)}(0) & 0 & \dots & 0 \\ h^{(i)}(1) & h^{(i)}(0) & \dots & 0 \\ \vdots & \dots & \dots & \vdots \\ h^{(i)}(N-1) & \dots & \dots & h^{(i)}(N-Q) \end{bmatrix} \begin{bmatrix} b^{(i)}(0) \\ b^{(i)}(1) \\ \vdots \\ b^{(i)}(Q) \end{bmatrix} \quad (3)$$

which may be rewritten as:

$$\underline{E}^{(i)} = \underline{X}^{(i)} \underline{a}^{(i)} - \underline{H}^{(i)} \underline{b}^{(i)}. \quad (4)$$

Equation (4) may be decomposed into two parts using the orthonormal projection matrix \underline{P} onto the column space of $\underline{X}^{(i)}$, as noted by McClellan and Lee [17], which leads to:

$$\underline{E}^{(i)} = \underline{P}^\perp \underline{X}^{(i)} \underline{a}^{(i)} + (\underline{P} \underline{X}^{(i)} \underline{a}^{(i)} - \underline{H}^{(i)} \underline{b}^{(i)}) \quad (5)$$

$$\text{with } \underline{P} = \underline{H}^{(i)} [\underline{H}^{(i)H} \underline{H}^{(i)}]^{-1} \underline{H}^{(i)H}$$

Recall that the IP iteration minimizes the expression $\|\underline{E}^{(i)}\|_2$, which leads to the following minimization problem [17]:

- (a) minimize $\underline{P}^\perp \underline{X}^{(i)} \underline{a}^{(i)}$ subject to $a^{(i)}(0) = 1$,
- (b) solve $\underline{b}^{(i)} = [\underline{H}^{(i)H} \underline{H}^{(i)}]^{-1} \underline{H}^{(i)H} \underline{X}^{(i)} \underline{a}^{(i)}$

Step (a) above may be rewritten as:

$$[\underline{C}, -\underline{d}] [a^{(i)}(P), \dots, 1]^T = \underline{0},$$

where

$$\underline{C} = \underline{P}^\perp \underline{X}^{(i)} [1:N, 1:P], \quad \underline{d} = \underline{P}^\perp \underline{X}^{(i)} [1:N, P+1].$$

Step (a) of the IP method has classically solved using the classical LS approach, which accounts for errors in \underline{d} only. However, errors occur both in \underline{C} and \underline{d} . A better fit of the data can be obtained by taking into account for errors in both in \underline{C} and \underline{d} , as the TLS set-up allows us to do. Thus, the TLS-Based IP iteration solves for (a) using a TLS approach [20], which leads to the following minimization problem:

- (a) Minimize $\underline{P}^\perp \underline{X}^{(i)} \underline{a}^{(i)}$ subject to $a^{(i)}(0) = 1$, using a TLS method.
- (b) solve $\underline{b}^{(i)} = [\underline{H}^{(i)H} \underline{H}^{(i)}]^{-1} \underline{H}^{(i)H} \underline{X}^{(i)} \underline{a}^{(i)}$.

3.2 Data Scaling

3.2.a Introduction

Van Huffel has shown that when errors in the TLS matrix and right-hand-side vector are uncorrelated with zero-mean and equal variance, then under mild conditions the TLS solution is a strongly consistent estimate of the true solution of the unperturbed system [4]. For the problem considered, errors in the data result from errors in the signal $x(n)$ to be modeled. Assuming the data to be modeled is distorted with Gaussian white noise, the errors in $\underline{H}^{(i)}$ are correlated as they are obtained as the output of an AR linear system. However, consistency in the TLS estimate may still be retained by using the Generalized TLS (GTLS), as proposed originally by Van Huffel [2,4,17]. Thus, data scaling is needed to insure diagonal error covariance matrices, and the problem becomes to estimate the error covariance matrices $\underline{F}^{(i)}$ and $\underline{G}^{(i)}$ at each iteration given by:

$$\begin{aligned} \underline{F}^{(i)} &= \underline{E}[\underline{N}^{H(i)} \underline{N}^{(i)}], \\ \underline{G}^{(i)} &= \underline{E}[\underline{N}^{(i)} \underline{N}^{(i)H}], \end{aligned}$$

where $N^{(i)}$ represents the errors (noise contribution) in $[C, \underline{d}]$ at iteration (i).

3.2.b Computation of the Matrix $F^{(i)}$

Assume that the noisy signal $x(n)$ is defined by $x(n) = s(n) + w(n)$, where $w(n)$ is wss white noise, and $s(n)$ is an ARMA signal. The noise correlation matrix $F^{(i)}$ may be expressed in terms of the correlation matrix $R_w^{(i)}$ obtained from the AR process $1/A^{(i)}(z)$:

$$\begin{aligned} F^{(i)} &= E[N^{(i)H} N^{(i)}] = E[(P^\perp W^{(i)})^H (P^\perp W^{(i)})] \\ &= E[W^{(i)H} P^\perp P^\perp W^{(i)}] \\ &= E[W^{(i)H} P^\perp W^{(i)}] = E[W^{(i)H} (I - P) W^{(i)}] \\ &= E[W^{(i)H} W^{(i)}] - E[W^{(i)H} P W^{(i)}] \\ &= R_w^{(i)} - E_w^{(i)} \end{aligned} \quad (6)$$

Computations show that the components of $E_w^{(i)}$ in equation (6) can be expressed as:

$$E_w^{(i)}(l, k) = \sum_{q, j=1}^n P_{qj} r_w^{(i)}(l + q - j - k), \quad (7)$$

where P_{ij} is the $(i, j)^{th}$ component of the projection matrix P defined earlier, and $r_w^{(i)}(n)$ is the correlation function obtained when passing the white noise $w(n)$ through the AR system with transfer function $1/A^{(i)}(z)$. Using the fact that the noise distortion $w(n)$ is assumed to be white, $r_w^{(i)}(|l + q - j - k|)$ is non zero only when $l + q - j - k = 0$. Thus, the double summation in equation (7) reduces to a single summation. Furthermore, the correlation function $r_w^{(i)}(k)$ can easily be computed using the results by Dugre et. al. [6] who proposed an algorithm to generate a covariance sequence from its AR coefficients.

3.2.c Computation of the matrix $G^{(i)}$

Again the error covariance matrix $G^{(i)}$ may be expressed in terms of the correlation matrix $R_w^{(i)}$ obtained from the AR process $1/A^{(i)}(z)$ obtained at iteration (i) by:

$$\begin{aligned} F^{(i)} &= E[N^{(i)} N^{(i)H}] = P^\perp E[W^{(i)} W^{(i)H}] P^\perp \\ &= P^\perp R_w^{(i)} P^\perp \end{aligned} \quad (8)$$

3.2.d GTLS Solution

Applying the results presented by Van Huffel, the general TLS-based IP iterative solution for $\underline{a}^{(i)}$ at iteration (i) is then given by solving:

$$(R_G^{(i)*}[C, -d](R_F^{(i)})^{-1}) \begin{pmatrix} a^{(i)}(P) \\ R_F^{(i)} \\ \vdots \\ a^{(i)}(1) \\ 1 \end{pmatrix} = \underline{Q} \quad \text{with } R_F^{(i)} = \text{chol}(F^{(i)}), \quad R_G^{(i)} = U \Sigma U^H,$$

with:

$$\Sigma = \text{diag}[\sqrt{\sigma_1}, \dots, \sqrt{\sigma_r}, 0, \dots, 0]$$

where r is the rank of $R_G^{(i)}$. Next, the estimate for $\underline{b}^{(i)}$ can be obtained by replacing $\underline{a}^{(i)}$ by its value in the expression:

$$\underline{b}^{(i)} = [H^{(i)H} H^{(i)}]^{-1} H^{(i)H} X^{(i)} \underline{a}^{(i)}$$

3.3 Simulation Results

The TLS-based IP method is implemented on time-series data generated by an ARMA(3,4) in additive white noise and its performances compared with that of the LS-based IP method. In both cases, initial estimates for the iterative procedures are obtained using Yule Walker equations for the poles and Shank's technique when solving for the zeros. The resulting noisy signal is modelled with an ARMA(5,6) using a sequence of length 60. The noise variance is chosen equal to 2 and the ARMA parameters are chosen equal to:

$$\begin{aligned} \underline{a}_p &= [1, -2, 1.6725, -0.4613] \\ \underline{b}_p &= [1, -0.9, 0.04, 0.3960, -0.2912] \end{aligned}$$

Figure 2.a shows the noise-free signal, the noisy signal, and the estimated signal obtained during the first 5 iterations using the classic IP method. Power spectral estimates obtained for the noise-free signal, the noisy signal, and that obtained with the initial ARMA coefficients estimated using Yule Walker equations and Shank's method, are shown in Figure 2.b. Figures 3.a and 3.b represent the same estimates obtained when using the proposed TLS-based IP scheme. Note that Figures 2 and 3 represent the best performances obtained during the first 5 iterations for both schemes. Figure 4 and 5 represent the true pole (a_p) and zero (b_p) locations, and estimated poles (a_{ip}) and zeros (b_{ip}) locations obtained when using the IP and TLS-based IP schemes. This example illustrates the fact that the bias in the estimated pole locations obtained using the TLS-based technique is usually smaller than that obtained using the LS-based IP method when the SNR is medium to high. However, we noted that when the SNR is low, no distinct improvement is noted consistently when using the proposed technique.

4. Conclusions

This study has investigated the application of the TLS problem in the Iterative Prefiltering method for time-domain ARMA modeling. Results show that the pole bias is usually smaller when using the TLS-based scheme than when using the classical LS-based IP method, when SNR are medium to high. We note that, similarly to the LS-based method, the TLS-based IP method is not

TLS-based IP method. The main drawback in the proposed TLS-based IP method is the computational load increase.





Figure 1.a) LS solution to $A\mathbf{x} = \mathbf{b}$; **b)** TLS solution to $A\mathbf{x} = \mathbf{b}$.




Figure 2.a) Noise-free signal, noisy signal, LS-based IP estimated signal; b) Spectra: $H_{\text{noise_free}}$: noise-free signal, H_{est} : LS-based IP signal, H_{it1} : initial estimate.




Figure 3.a) Noise-free signal, noisy signal, TLS-based IP estimated signal; **b)**Spectra: $H_{\text{noise_free}}$: noise-free signal, H_{est} : TLS-based IP signal, H_{it1} : initial estimate.






Figure 4. True pole (a_p) and zero (b_p) locations; LS-based IP estimated pole (a_{ip}) and zero (b_{ip}) locations.




Figure 5. True pole (a_p) and zero (b_p) locations; TLS-based IP estimated pole (a_{ip}) and zero (b_{ip}) locations.

References

- [1] G.H. Golub & C.F. Van Loan, Matrix Computations, 2nd Ed., John Hopkins University Press, 1989.
- [2] S. Van Huffel & J. Vanderwalle, The Total Least Squares Problem: Computational Aspects and Analysis, SIAM, 1991.
- [3] E.M. Dowling & R.D. DeGroat, "The Equivalence of the Total Least Squares and the Minimum Norm Methods," IEEE Trans. on SP, Vol. 39, No. 8, Aug. 1991, pp. 1891-1892.
- [4] S. Van Huffel "The Generalized Total Least Squares Problem," NATO ASI Series, Vol. F70, Springer Verlag, 1991.
- [5] S. Van Huffel & J. Vanderwalle, "Analysis and Properties of the Generalized Total Least Squares Problem $AX=B$ when Some or All Columns in A are Subject to Errors," SIAM J. Matrix Appl., Vol. 10, No. 3, July 1989, pp. 294-315.
- [6] J.P. Dugre, A.A. Beex, & L.L. Scharf, "Generating Covariance Sequences and the Calculation of Quantization and Rounding Errors variance in Digital Filters," IEEE Trans. on ASSP, Vol. ASSP-28, No. 1, Feb. 1980, pp. 102-104.
- [7] S. Van Huffel, "Analysis and Solution of the Nongeneric Total Least Squares Problem," SIAM Matrix Anal. Appl., Vol. 9, No. 3, July 1988, pp. 360-372.
- [8] P. Stoica, T. Soderstrom, & S. Van Huffel, "On the Equivalence of SVD and TLS based Yule-Walker approaches to Frequency Estimation," Signal Processing VI, 1992, pp. 669-672.
- [9] Y. Hua & T.P. Sarkar, "On the Total Least Squares Linear Prediction Method for Frequency Estimation," IEEE Trans. on ASSP, Vol. ASSP-38, No. 12, Dec. 1990, pp.2186-2189.
- [10] C.E. Davila, "Total Least Squares System Identification and frequency Estimation for Overdetermined Model Orders," ICASSP Proc., April 1993, pp. IV468-471.
- [11] P. Stoica, T. Soderstrom, & S. Van Huffel, "On SVD-Based and TLS-Based High-Order Yule-Walker methods of Frequency Estimation," Signal Processing, Vol. 29, 1992, pp. 309-317.
- [12] K.S. Arun, "A Unitarily Constrained Total Least Squares Problem in Signal Processing," SIAM Matrix Anal. Appl., Vol. 13, No. 3, July 1992, pp. 729-745.
- [13] P.M. Rands Jensen & K. Hermansen, "Application of SVD to AR Spectral Estimation," Signal Processing VI, 1992, pp. 763-766.
- [14] S. Van Huffel & J. Vanderwalle, "Subset Selection Using the Total Least Squares Approach

- in Collinearity Problems with Errors in the Variables," Linear Alg. and its Appl., Vol. 88, No. 89, 1987, pp. 695-714.
- [14] S. Van Huffel & J. Vanderwalle, "Comparison of Total Least Squares and Instrumental Variable Methods for Parameter Estimation of Transfer Function Models," Int. J. Control, Vol. 50, No. 4, 1989, pp. 1039-1056.
 - [15] K. Steiglitz & L.E. McBride, "A Technique for the Identification of Linear Systems," IEEE Trans. on Aut. Cont., 1965, pp. 461-464.
 - [16] K. Steiglitz, "On the Simultaneous Estimation of Poles and Zeros in Speech Analysis," IEEE Trans. on ASSP, Vol. ASSP-25, No. 3, June 1977, pp. 229-239.
 - [17] J.H. McClellan & D. Lee, "Exact Equivalence of the Steiglitz-McBride Iteration and IQML," IEEE Trans. on SP, Vol. 39, No. 2, Feb. 1991, pp. 509-512.
 - [18] B. De Moor, "Total Least Squares for Affinely Structured Matrices and the Noisy Realization Problem," Int. Report, ESAT-SISTA/TR 1993-21, Katholieke Universiteit Leuven, Leuven, Belgium.
 - [19] T.P. Johnson, ARMA Modeling Methods for Acoustic Signals, MSEE Thesis, Naval Postgraduate School, March 1992.
 - [20] M.P. Fargues, "TLS-Based Iterative Prefiltering for ARMA Modeling," 3rd SIAM Conference on Linear Algebra, Signals, Systems, and Control, Aug. 16-19, 1993, Seattle, WA.

INITIAL DISTRIBUTION LIST

	No. Copies
1. Defense Technical Information Center Cameron Station Alexandria, VA 22304-6145	2
2. Dudley Knox Library, Code 52 Naval Postgraduate School Monterey, CA 93943-5101	2
3. Chairman, Code EC Department of Electrical and Computer Engineering Naval Postgraduate School Monterey, CA 93943-5121	1
4. Professor Monique P. Fargues, Code EC/Fa Department of Electrical and Computer Engineering Naval Postgraduate School Monterey, CA 93943-5121	5